

marantz®



SR7013

9.2 CHANNEL NETWORK AV RECEIVER WITH UNIQUE AURO-3D AND IMAX ENHANCED



Enjoy three-dimensional audio and advanced video processing with the 9.2 channel Marantz SR7013. For superior music quality, Marantz-unique HDAM circuit technology provides optimal fidelity and dynamic range of high-resolution files. Stream music from Spotify, TIDAL, Deezer, Amazon Music and more with built-in Bluetooth, HEOS or AirPlay 2, and control it all with Amazon Alexa voice compatibility.

Highlights

Your Benefits

| | |
|---|--|
| 9.2 channel AV Receiver with 200W per channel; 11.2ch processing | Enough power to fill big rooms with renowned Marantz sound |
| Dolby Atmos and DTS:X (up to 7.1.4 with external 2ch amplifier), Auro-3D | Immersive 3D sound with effects from overhead |
| IMAX Enhanced audio decoding (update) | Offers a new level of quality in immersive sight and sound experiences |
| Marantz sound tuning with all-new components, including current feedback HDAM pre-amplifier section | Designed for purity with both movies and music for all-round entertainment capability |
| High performance AKM AK4458 192kHz/32bit D/A converters for all channels | Highest resolution for music and movie sound |
| Audyssey MultEQ XT32, LFC, Sub EQ HT, Dynamic Volume and Dynamic EQ | Delivering the ultimate equalization for your individual room |
| Built-in WiFi with 2.4GHz/5GHz dual band support | Improved network stability especially in WiFi-crowded environments |
| AirPlay, Bluetooth, Internet Radio, Spotify Connect, TIDAL, Deezer | Access to almost unlimited online music sources |
| Network Streaming: DSD (2.8/5.6MHz), FLAC, ALAC and WAV support | High Resolution audio streaming for HiFi enthusiasts |
| HEOS Music Streaming Technology and the HEOS App | Comfortable control of music sources, and multi-room experience with other HEOS products |
| 4K/60 Hz, 4:4:4, HDR and BT.2020, Dolby Vision compatible, HLG | Latest HDMI standard for future-proof compatibility |
| 8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support; 3 HDMI outputs (zone) | Plenty of inputs for your digital devices; different video in different rooms |
| eARC (Enhanced Audio Return Channel) | Allows 3D audio transmission from TV via HDMI audio return channel |
| Colour-coded speaker terminals, Setup Assistant, Marantz AVR Remote App | Hassle-free installation, setup and operation |
| Advanced Multi-Room options; 11.2ch Pre-out; RS232 Control; Crestron Connected, IP-control | Audio and video in multiple rooms; ready for 3rd Party Home Automation systems |



because music matters

SR7013

9.2 CHANNEL NETWORK AV RECEIVER WITH UNIQUE AURO-3D AND IMAX ENHANCED



| FEATURES | SR7013 |
|---|----------------------------------|
| MULTICHANNEL SURROUND | |
| DTS HD Master / DTS:X / DTS Neural:X | • / • / • |
| Dolby TrueHD / Dolby Atmos / Dolby Surround | • / • / • |
| Auro-3D / Auromatic | • / • |
| Multichannel Stereo | • |
| IMAX Enhanced | • |
| Compressed audio Enhancer: MDAX2 | • |
| Audyssey | MultEQ XT32 with LFC/Sub EQ HT |
| Audyssey Dynamic EQ / Dynamic Volume | • / • |
| Audyssey MultEQ Editor App support | • |
| NETWORK / SOURCES | |
| Network Audio Streaming | • |
| HEOS Multiroom integrated | • |
| Works with Amazon Alexa | • |
| Lossy formats MP3 / WMA / AAC | • / • / • |
| Lossless formats FLAC / ALAC / WAV | • / • / • |
| DSD Streaming | • (2.8 MHz / 5.6 MHz) |
| FLAC HD 192/24 / WAV 192/24 / ALAC 192/24 | • / • / • |
| Gapless playback | • (FLAC, WAV, ALAC, DSD) |
| AirPlay 2 audio streaming | • |
| Internet Radio (TuneIn) | • |
| Spotify Connect, Deezer, TIDAL, Napster, Soundcloud * | • / • / • / • / • |
| Compatible with Remote APP for Smart Phones | Android/iOS |
| Ethernet / Wi-Fi | • / • (dual antenna / dual band) |
| Network: (IP-control / update) | • / • |
| Front Inputs: HDMI / USB | • / • |
| USB Audio | • |
| FM / AM Tuner | • / • |
| Bluetooth | • |
| HDMI | |
| 4K 60Hz 4:4:4 resolution / HDCP 2.2 | • / • |
| eARC (Enhanced Audio Return Channel) | • |
| Dolby Vision compatible / Hybrid Log Gamma (HLG) | • / • |
| HDMI pass through on stand-by | • |
| 3D video pass through | • |
| Video conversion | CVBS / HDMI; Comp / HDMI |
| Video processing and -scaling | 1080p, 4K 60/50Hz |

* This feature is not available in all countries.

D&M Europe B.V.
A Division of Sound United
Beemdstraat 11
5653 MA Eindhoven
The Netherlands

| INPUTS/OUTPUTS | | | |
|---|-------------|-------------------------------|------------|
| VIDEO | | | |
| Composite In / Out | | 3+1 / 2 | |
| Component In / Out | | 3 / 1 | |
| HDMI In / Out | | 7+1 / 3 (2 main + 1 zone) | |
| AUDIO | | | |
| Analogue In / Out | | 5+1 / 0 | |
| Digital Optical In | | 2 | |
| Digital Coaxial In | | 2 | |
| Multichannel Pre Out | | • (11.2 with 11.2 processing) | |
| Zone audio preout | | 2 | |
| Subwoofer Out | | 2 | |
| 7.1 Multichannel input | | • | |
| SPECIFICATIONS | | | |
| Number of poweramps | | 9 | |
| Power Output per channel | | | |
| 6 ohm, 1 kHz, 1%, 1ch Drive | | 200 W | |
| 6 ohm, 1 kHz, 0.7%, 2ch Drive | | 165 W | |
| 8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive | | 125 W | |
| Audio Signal to Noise Ratio | | 102 dB | |
| GENERAL | | | |
| Available colours: Black / Silver-Gold | | • / • | |
| System Remote Control | | RC036SR | |
| Power Consumption in W | | 710 | |
| Power Consumption No-Sound (ECO ...on/off) in W | | 65 / 110 | |
| Standby Consumption in W | | 0.2 (with CEC 0.5) | |
| Maximum Dimensions (W x D x H) in mm | | 440 x 411 x 185 | |
| Weight in kg | | 14.2 | |
| EAN | | | |
| EU | SR7013/N1B | 4951035065983 | Black |
| | SR7013/N1SG | 4951035066027 | Silvergold |
| UK | SR7013/T1B | 4951035066546 | Black |
| | SR7013/T1SG | 4951035066553 | Silvergold |



The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

* All specs can be subject to change.